

CERES RACK Series

1~3kVA online Rack UPS



Power range

1~3kVA

Operation

1P/1P, online double conversion

Applications

- Government, Finance, IT,
- Education, Transportation,
- Broadcasting, Medical,
- Energy, etc.

Characteristics

- High efficiency up to 96%.
- Output PF=1, high load adaptability.
- Wide input voltage range of 110~300Vac.
- Max charging current up to 12A.

Model	CERES SR-1K	CERES SRK-1K	CERES SR-2K	CERES SRK-2K	CERES SR-3K	CERES SRK-3K
Rate Power	1kVA/1kW	1kVA/1kW	2kVA/2kW	2kVA/2kW	3kVA/3kW	3kVA/3kW
Cold start	Default output 50/60Hz					
Input voltage range	110~300VAC;100% load@176VAC~276VAC, 100%~50% power derating@110VAC~176VAC, 50% load@276VAC~300VAC					
Input power factor	≥0.99					
Frequency range	50/60±5Hz(default),±3Hz/±10Hz(settable)					
Output power factor	1.0					
Output	Rate voltage	220/230/240VAC, 200/208VAC(PF=0.9)				
	Load response	≤5% (0% - 100% -0% step load)				
	Recovery time	≤40ms (0% - 100% -0% step load)				
	Output THDu	≤2% , Linear load ; ≤ 5% non-linear load according to IEC62040-3				
Transfer time	Main to BAT	0				
	INV to BYP	4ms				
Efficiency (normal mode)	Max 96%					
Noise (1 meter)	43dB@<60%load, 47dB@>60%load		<50dB@<60%load,<55dB@>60%load		<50dB@<60%load,<55dB@>60%load	
	Normal	102%~110%: 30mins, 110%~125%:10mins, 125%~150%: 30 seconds				
	Battery mode	102%~110%: 1min, 110%~125%: 10 seconds, 125%~150%:5 seconds				
Bypass mode	<130%: long time, 130%~150%:10mins, 150%~180%:5 seconds					
Battery	Model	12VDC/7Ah	Depend on external battery	12VDC/7Ah	Depend on external battery	12VDC/9Ah
	Quantity	3		6		6
	Max charging	1A	1-12A(settable)	1A	1-12A(settable)	1A
	Rate voltage	36VDC		72VDC		72VDC
Standard	EPO, RS232					
Option	SNMP card,AS400, USB, RS485, BMS by dry contact, Air filter					
Dimension ,W*D*H(mm)	440*440*86		440*580*86		440*440*86	
Weight (kg)	19	9.5	27.5	9.7	28	10

Statement: The products will continue to be innovative and optimized, which may lead to asynchronous updates of the actual product and promotional materials. Therefore, this document is for reference only and does not constitute any offer or commitment.